



NATURE POWER 3000 WATT POWER INVERTER



Features

Convert battery power to household AC power

- 4 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- 3000 Watts Continuous Output, 6000 Watts Surge
- Battery Voltage and Output Power Indicate Light
- Comes With Battery Connect Cables
- Remote Control Available (Remote Control Sold Separately)
- Compact Size



SPECIFICATIONS

AC OUTPUT

Power: 3000W (Continuous), 6000W(Peak)

Voltage: 115±10% Vac

Frequency: 60±3 Hz

Waveform: Modified sinewave

AC Outlet: 4 x 3Prong AC outlet

DC OUTPUT

USB: 2 x 5V/2A

DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.0-15.0Vdc

Material: ABS, Stell, Aluminum

PROTECTION:

Input Undervoltage Warning: 10.5±0.5Vdc

Input Undervoltage Shutdown : 10.0±0.5Vdc

Input Overvoltage Shutdown: 15.5±0.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

SHIPPING DETAILS

Item Number: 37003

UPC Code: 839290003299

Original: Taiwan

Product Dims LxWxH: 13.3 x 10.4 x 4.6 in

Color box Dims LxWxH: 18.5 x 12.8 x 7.7 in

Product Weight: 15.5 lbs with package

11.1 lbs without package

Master Quantity: 2

Master Dimensions: 27.2 x 18.5 x 9.3 in

Master Weight: 31.8 lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

