



NATURE POWER 1500 WATT POWER INVERTER



Ground wire
15AWG, 1x39.3"

Battery Cable
6AWG, 2x39.3"

Features

Convert battery power to household AC power

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- 1500 Watts Continuous Output, 3000 Watts Surge
- Comes With Battery Connect Cables
- Remote Control Available (Remote Control Sold Separately)
- Compact Size

SPECIFICATIONS

AC OUTPUT

Power: 1500W (Continuous), 3000W(Peak)

Voltage: 115±10% Vac

Frequency: 60±3 Hz

Waveform: Modified sinewave

AC Outlet: 2 x 3Prong AC outlet

DC OUTPUT

USB: 1 x 5V/2A

DC INPUT

Voltage (nominal): 12.8-13.2Vdc

Operation Range: 10.0-15.0Vdc

Material: ABS, Stell, Aluminum

PROTECTION:

Input Undervoltage Warning: 10.5±0.5Vdc

Input Undervoltage Shutdown : 10.0±0.5Vdc

Input Overvoltage Shutdown: 15.5±0.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes



SHIPPING DETAILS

Item Number: 37015

UPC Code: 839290003275

Original: Taiwan

Product Dims LxWxH: 8.27 x 6.7 x 3.54 in

Color box Dims LxWxH: 10.43 x 10 x 4.8 in

Product Weight: 7.1 lbs with package

4.5 lbs without package

Master Quantity: 4

Master Dimensions: 22.1 x 12.6 x 12.4 in

Master Weight: 29 lbs



1-800-588-0590

www.naturepowerproducts.com



fb.me/NaturePowerProducts

